

# ECLIPSE STEP LIGHTS

## INSTALLATION INSTRUCTIONS AND WARRANTY INFORMATION

**!** **IMPORTANT** Read all instructions before installing plate. Retain for future reference.

**SAFETY:** Turn the power at off main fuse/breaker panel before attempting any electrical work. This luminaire must be wired in accordance with local electrical codes and ordinances. Grounding connections should be done in the detachable junction box.


**⚠ WARNING:** Make sure the power is OFF from the electrical panel before starting or installation attempting any maintenance.

	Model	G-48200	G-48210	G-48220	
DRIVER	Input	120V AC 60Hz			
	Output	36V DC 110mA CC			
	Lamp Life	50,000 Hours			
	Operating Temperature	-40°C to +40°C			
	Dimming	Triac Dimming			
	DC Wire Type	FT6 DC Wire			
	Wire Space	4.8 Cubic inch			
LIGHT	Energy used	5 W			
	Luminous Flux	350 LM	350 LM	200 LM	
	Equivalent to:	40W halogen	40W halogen	20W halogen	
	CCT Options	27K-30K-35K-40K-50K			
	Beam Angle	40 Degree			
	CRI	Ra>90			
	Approved Location	Wet			
MOUNTING	OD	2.76"(70mm)	4.96"X3.15" (126mmX80mm)	4.96"X3.07" (126mmX78mm)	
	ID	1.18"(30mm)	2.24"X1.38" (57mmX35mm)	1.77"X1.61" (45mmX41mm)	
	Height	1.29"(32.8mm)	1.29"(32.8mm)	1.5"(38mm)	
	Cut Out	2.36"(60mm)	3.08"X1.97" (78mmX50mm)	2.56"X2.56" (65mmX65mm)	


Dimmer Compatibility List for LED Recessed Lights. Dimmable down to 10%				
Brand	Family	Model	Load (W)	G-48200/G-48210/G-48220
LUTRON	Skylark Contour	LECL-153P	150W	1-29
		CTCL-150H	150W	1-29
		LGCL-153PLH	150W	1-29
		CTCL-153P	150W	1-29
		SCL-153P	150W	1-29
	Caseta	S-600P	600W	1-39
		PD-6WCL	600W	1-39
		PD-5NE	150W	1-29
LEVITON	PD-10NXD	250W	1-39	
	DIVA	DVCL-153P	150W	1-29
	Toggler	TGCL-153P	150W	1-29
	Ariadni	AYCL-153P	150W	1-29
EATON	Maestro	MACL-153M	150W	1-29
	Illumatech	IPL06	150W	1-29
	SureSlide	6672	150W	1-29
EATON	Smart Dimmer	AAL06	300W	1-39

## Installation

1. Nail-in the mounting plate to the ceiling joist. Measure the position of the opening on the mounting plate from each wall.
2. Install the drywall on to the wall.
3. Open a hole where the mounting plate opening located accordind to the cutout template dimensions. (Fig.1)
4. Pull the supply wire through the cut-out hole. Do the electrical supply connection in the detachable junction box. (Note: A licensed electrician must do the connections as per the local electrical code). (Fig.2)
5. Insert the junction box into the wall. (Fig.3)
6. Do the connection to the luminaire and close the quick connect box. (Fig.3)
7. **New construction applications:** Hardwire box shall be firmly secured to studs,joists, or similar fixed strucatural units  
**Remodel applications:** Do not require the hardwire box to be firmly secured after the mounting paltes,stud,joists or structural units that have been concealed. Snap off the hardwire box tabs then insert into wall.
8. Push the spring clips upwards and push the luminaire into the cut hole of the wall. Release the spring clips and align the luminaire to sit properly over the wall cut hole. (Fig.4)
9. Switch on the supply breaker and turn on the luminaire.



Compatible fixtures / luminaires compatibles



**Triac DIMMING (120V only):** We recommended LED/CFL dimmers that have a low range adjustment dial. After all fixtures are connected to the dimmer, adjust the dial to the lowest position before the lights start to flicker or shut down. This setting depends on the local voltage and number of fixtures per dimmer. For a typical LED dimmer rated for 150W LED load the maximum number of fixtures per dimmer.

**WARNING: DO NOT USE ANY OTHER DRIVERS EXCEPT THE DRIVERS THAT ARE INCLUDED WITH THE FIXTURE. DO NOT CONNECT MULTIPLE FIXTURES TO ONE DRIVER. DO NOT OPEN THE LIGHT FIXTURE OR THE SIDE PLATES OF THE DRIVER - NO SERVICEABLE PARTS INSIDE.**

#### MANUFACTURER'S LIMITED WARRANTY

Your Product, when delivered to you in new condition and in original packaging, is warranted against defects in materials and workmanship as follows for a period of 3 years from the date of the original purchase. Defective products returned and proven to be defective upon inspection will be repaired, replaced with a new Product or a credit will be issued against original invoice at the discretion of manufacturer.

To avoid any doubt, "the replacement Product" does not include any removal or installation costs or expenses, including without limitation labor costs or expenses, shipping costs to return defective products or any damages that may occur during the return of product. This limited warranty is subject to the following additional conditions:

1. Products must have been installed and operated in accordance with manufacturer's instructions.
2. Products have not been subjected to accident, neglect, abuse, misuse, lightning, electrical surges or acts of God.
3. The Product has been purchased directly from an authorized distributor.
4. Purchase receipt or invoice is available for inspection.
5. This warranty is limited to Products purchased for use in regions that are within jurisdiction of Canada and USA.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received, including interference that may cause undesired operation.

THE FOREGOING WARRANTY IS EXCLUSIVE, AND THE SOLE REMEDY FOR ANY AND ALL CLAIMS. IN NO EVENT WILL THE MANUFACTURER BE LIABLE FOR ANY SPECIAL, COMPENSATORY, INDIRECT, PUNITIVE, OR INCIDENTAL OR CONSEQUENTIAL DAMAGES INCLUDING, WITHOUT LIMITATION, DAMAGES RESULTING FROM LOSS OF USE, PROFITS, BUSINESS OR GOODWILL, WHETHER OR NOT THE MANUFACTURER HAS BEEN ADVISED OF THE POSSIBILITY THEREOF.