

INSTALLATION INSTRUCTIONS FOR CABLE VERSION LED PENDANT

IMPORTANT: Read all instructions before installing LED downlight. Retain the instructions for future reference.

SAFETY: This fixture must be wired in accordance with local electrical codes and ordinances. Carefully observe grounding procedure under installation. All work should be done by a qualified electrician.

INSTALLATION STEPS:

1. Turn off the power from the electrical panel before starting installation.
2. Remove the screws installed at side of the flushmount panel.
3. Install mounting bracket onto the outlet box using the supplied screws.(Fig.1)
4. Connect power supply wires to the surface mount panel wires with wire nuts. Make certain no exposed strands of wire.(Fig.2)
 - A. Connect green ground wire of power supply to green wire of surface mount panel green wire.
 - B. Connect the white wire of power supply to the white wire of surface mount panel green wire.
 - C. Connect the black wire of power supply to the black wire of surface mount panel green wire.
- Remark:** If using 0-10V dimmer, connect dimming wire to the two wire connector by wire nuts. Connect the purple wire (Dim+) to the purple wire(Dim+), Connect the pink wire (Dim-) to the pink wire(Dim-)
5. Unscrew the screw with supplied screw driver and adjust your desired cable length. Then fasten the screws well.(Fig.3)
6. Attach the flushmount panel to the mounting bracket by fastening the canopy using the screws removed at the step 2.(Fig.4)
7. Choose the required correlated color temperature(CCT) by the CCT switch on the back of the cylinder module.(Fig.5)
8. Plug-in the quick connectors to the cylinder module connectors accordingly.
9. Twist the cylinder module clockwise onto the flushmount panel.(Fig.6)
10. Once installation is complete, turn on the power to confirm fixture is working properly. (Fig.7)

